

IEEE P802.15
Wireless Personal Area Networks

Project	IEEE P802.15 Working Group for Wireless Personal Area Networks (WPANs)	
Title	Comment Resolution for some TG4m TVWS-FSK PHY related comments	
Date Submitted	March. 19, 2013	
Source	[Alina Lu Liru, Keiichi Mizutani, Ryuhei Funada, Chin Sean Sum, Ming-Tuo Zhou, Fumihide Kojima, Hiroshi Harada(NICT), Cristina Seibert(SSN)]	Voice: [[+81-46-847-5294] Fax: [[+81-46-847-5440] E-mail: [liru@nict.com.sg]
Re:	Submission for comment resolution in LB87 of IEEE 802.15.4m draft	
Abstract	Comment Resolution for the TVWS-FSK PHY related comments	
Purpose	Resolve TVWS-NB-OFDM related comments in LB87	
Notice	This document has been prepared to assist the IEEE P802.15. It is offered as a basis for discussion and is not binding on the contributing individual(s) or organization(s). The material in this document is subject to change in form and content after further study. The contributor(s) reserve(s) the right to add, amend or withdraw material contained herein.	
Release	The contributor acknowledges and accepts that this contribution becomes the property of IEEE and may be made publicly available by P802.15.	

CID341: Table 133 should spell out Parameter and put parentheses around (h) for modulation index; implication of table is that modulation index 0.5 or 1.0 allows interoperability - is this true?

Recommend solution: Make changes to table 133 for clarity. Ensure that modulation index can truly be grouped as 0.5 or 1.0

Proposed resolution: Accept

Table 133—TVWS-FSK modulation and channel parameters^a

Param	Mode #1		Mode #2		Mode #3		Mode #1	Mode #1
Data rate (kb/s)	50		100		200		300	400
Modulation level	2-level		2-level		2-level		2-level	4-level
Modulation index h	0.5	1	0.5	1	0.5	1	0.5	0.33
Channel spacing (kHz)	400	600	400	600	400	600	600	600

^aData rates shown are over-the-air data rates (the data rate transmitted over the air regardless of whether the FEC is enabled).

CID343: Bit to Symbol mapping is the last "function" of Figure 114. The order of these sections seems arbitrary - should they not flow like the reference modulator diagram?

Recommend solution: Reorder the sections to match Figure 114

CID344: Recommend that there be two sub sections in the paragraph: "For 2 level:" and "For 4 level".

Recommend solution: Consider making subsections

CID345: Bit to Symbol mapping is the last "function" of Figure 114. The order of these sections seems arbitrary - should they not flow like the reference modulator diagram?

Recommend solution: Reorder the sections to match Figure 114

CID355: Table 134 should explain the 4-level encoding for the SHR more clearly.

Recommend solution: Show that symbol 01 is 0 for the SHR and 11 is 1 for the SHR

Proposed resolution: Accept. The proposed changes are as follows.

20.1.2.2 Forward error correction (FEC)

FEC support is optional. The use of FEC is controlled by the PIB attribute *phyFECEnabled*, as defined in 9.3. The FEC scheme shall be according to sub-clause 19.2.2.4.

20.1.2.3 Code-symbol interleaving

Interleaving support is optional. The use of interleaving is controlled by the PIB attribute *phyInterleavingEnabled*, as defined in 9.3. Interleaving shall be according to sub-clause 19.2.2.5.

20.1.2.4 Data whitening

Data whitening is optional. The use of data whitening is controlled by the PIB attribute *phyWhiteningEnabled*, as defined in 9.3. The data whitening algorithm shall be as defined in 19.2.3.

20.1.2.5 Spreading

Spreading support is optional. The use of spreading is controlled by the PIB attribute *phySpreadingEnabled*, as defined in 9.3. The spreading method shall be as defined in 19.2.2.6.

20.1.2.6 Bit-to-symbol mapping

The symbol encoding is shown in Table 134.

- For 2-level Filtered FSK, the frequency deviation, f_{dev} , is equal to (symbol rate x modulation index)/2.
- For 4-level Filtered FSK modulation, the frequency deviation, f_{dev} , is equal to (3 x symbol rate x modulation index) / 2. Two bits shall be mapped to four frequency deviation levels for the PHR and PSDU.

The SHR shall always be encoded using 2-level modulation as specified in Table 134.

Table 134 -- TVWS FSK Symbol Encoding

2-level	
Symbol(Binary)	Frequency deviation
0	$-f_{dev}$
1	$+f_{dev}$
4-level	
Symbol(Binary)	Frequency deviation
01	$-f_{dev}$
00	$-f_{dev}/3$
10	$+f_{dev}/3$
11	$+f_{dev}$

20.1.3 Modulation quality

The modulation quality shall be as given in 18.1.2.3.